Subnetworks: Inquire Calling Job or Called Network

You can use this API to:

- find the current subnetwork for a job of type NET;
- find the current job calling a subnetwork.

Use the following statement:

```
CALLNAT 'NOPUSN1N'
    P-FUNCTION P-RC P-OWNER P-NETWORK P-RUN P-JOB
```

Meaning of the parameters:

Parameter	Format	Use		
P-FUNCTION	A01	in	Function code	
			C	Find calling job (available for active subnetworks only).
			S	Find subnetwork.
			T	Find the topmost calling job (available for active subnetworks only). This function recursively goes back in the subnetwork hierarchy, until the caller job is no longer part of a subnetwork.
P-RC	N03	out	Return code	
			0	Function OK.
			1	Input object not found.
			2	Wrong job type.
			3	Not a calling job.
			101	Invalid function code.
			102	Parameter missing.
P-OWNER	A10	mod	Owner of the network.	
P-NETWORK	A10	mod	Network.	
P-RUN	P13	mod	Run number. If the function "S" is used for a master job, this parameter must be zero.	
P-JOB	A10	mod	Job.	

The parameters P-OWNER, P-NETWORK, P-RUN and P-JOB are input and output parameters. They are overwritten with the values found by the API. Therefore the caller must supply these fields with new entries before each new call.